

6 Zones Mixer Amplifier



Brand: Secuview

Model no: SV-1506S



Main features

- ✓ Support USB/SD/MP3/AM & FM/Bluetooth/schedule player
- ✓ 6 zones output with separated switch control
- ✓ 4.3" TFT capacitance touch screen.
- ✓ Touch and button-pressing control. Can operate with physical buttons when touch screen is broken
- ✓ Built-in 4G MP3 program memory.
- ✓ Built-in radio; It can be manually / automatically searched and can store 40 radio channels.
- ✓ Built-in Bluetooth receiver module.

Rated Power	150W
Speaker Outputs	70V
Harmonic Distortion	<0.5% (1kHz, 1/3 rate power)
AUX Output	100Ω, 1V (0dBV)
Input	Mic: 600Ω; 8mV (±10%), unbalanced Line: 10kΩ, 300mV (±10%), unbalanced
Line Freq. response	50Hz-20kHz (±3dB)
Mic. Freq. response	40Hz-16kHz (±3dB)
Harmonic distortion	<0.5% (1kHz, 1/3 rated power)
S/N Ratio	Mic: 70dB Line: 80dB
AUX frequency response	70hz-16khz(+3dB)
Tone	Bass: ±10dB (100Hz) Treble: ±10dB (10kHz)
Protection	AC fuse, DC output protection, overload protection
Power supply	AC220-240V/50-60Hz
Power Consumption	220W
Size (LxWxH)	418x338x88mm