

60w Mixer Amplifier



Brand: Secuview

Model no: SV-MP600



Main features

- ✓ 60W RMS output (35W/60W available)
- ✓ 3 MIC inputs, 1 EMC input, 2 line inputs, 1 line output
- ✓ Support both 100V/70V and 4Ω 16Ω outputs
- ✓ With USB, FM and Bluetooth function
- ✓ Equipped with remote controller
- ✓ Bass & treble 2 tones control.
- ✓ 3 priority level: EMC>MIC1>others
- ✓ Support AC & 24V DC power supply

Rated Power	60W
Power	AC-110-240V
MIC1 input sensitivity	5mV
MIC2 input sensitivity	5mV
MIC3 input sensitivity	5mV
AUX1 input sensitivity	300mV
AUX2 input sensitivity	300mV
EMC input sensitivity	300mV
MIC frequency response	80Hz-10khz(+3db)
AUX frequency response	70hz-16khz(+3dB)
Noise	<5mV (4ohm load output terminal)
Distortion	<1% 1KHz
Treble adjustment	10dB (+2)
Bass adjustment	10dB (+2)
AC power	AC230V
Rated power	60W 4ohm load, AC230V/DC24V
Speaker output	70V, 100V, 4-16ohm